



CUSTOMER: _____

RFQ/Spec: _____

ERMCO Quote#: 568835

For detail information about the transformer, refer to the ERMCO quote documents.

Quote

Item	kVA	A	B	C	D	E	F	G	H	J	K	L	M	N
1	500	49	66.5	20	47.5	54.5	36.5	29.5	27	6	5	31	8	6.33
2	750	63	66.5	24	55.5	62.5	36.5	29.5	27	6	5	46	8	6.33
3	750	63	66.5	24	53.5	60.5	36.5	29.5	27	6	5	46	8	6.33
4	1000	63	66.5	24	55.5	62.5	36.5	29.5	27	6	5	46	8	6.33
8	2500	68	75.5	24	61.5	80.5	39.5	35.5	27	6	5	46	8	6.33

STANDARD FEATURES

- 1 HV Bushing
- 2 Lifting Lugs
- 3 Bolted Cover
- 4 1" Upper Fill Plug
- 5 Pressure Relief Valve
- 6 Nameplate
- 7 Hinged Top Cabinet
- 8 LV Bushing
- 9 Drain Valve w/Sampler

Quote

Item	P	Q	Wt (lbs)	Oil (gn)
1	53	N/A	4762	196
2	63	N/A	8213	362
3	57	N/A	7237	329
4	63	N/A	9305	350
8	73	N/A	13957	534

3 Phase Quotation Drawing
 For Dimensional Purposes Only
 All Features and Accessories Not Shown



ISSD BY: KA DATE: 03/05/20

REV ISSUE DATE: SCALE: NTS